

Job Information

Job #: 94135 Date:

Priority: — Authorized OT: No Authorized by:

Customer Information

Name: SFI Motor#:

Name Plate Information

Manufacturer: Us Enclosure: Open Drop Proof Horsepower/kW: 100

(ODP)

Serial#: RODP Model#: H016X06X118R08 Service Factor: 1.15

OM

Frame: 404TS Rated RPM: 1775 Rated Voltage: 460

Phase: 3 Rated Amps: 119.9 Cycles: 60

Special design: No



AC Electrical Inspection

Megs at reassembly: Good Surge at reassembly: Good Hi-pot reassembly: Good

Winding Resistance Incoming

Phases A to B Phases B to C Phases C to A Resistive imbalance

Outgoing 85.532 85.071 85.246 0.3

Test Run Inspection

Date April 30, 2018

— I have merged this motor and verified that all electrical tests are complete!

Power Supply

Phase A Phase B Phase C

No Load Voltage

No Load Current

Temperatures: (Degrees Fahrenheit)

Test run ball-bearing motors for 15 minutes.

Test run sleeve bearing motors for 60 minutes.

Temperature rise at the end of test run should be less than 2° every five minutes.



Test Run Inspection (Continued)

Ambient Temp:				
TIME	DE	Degree Change	ODE	Degree Change
START:				
5 MIN:				
10 MIN:				
15 MIN:				
20 MIN:				
25 MIN:				
30 MIN:				
35 MIN:				
40 MIN:				
45 MIN:				
50 MIN:				
55 MIN:				
60 MIN:				



Test Run Inspection (Continued)

Vibration Data: In./Sec-Peak (Readings should be less than .08 In/Sec Peak)

Horizontal VDE Axial

DE 0.06 0.15

ODE 0.02 0.14

Magnetic Center Measurements (Only Applies to Sleeve Bearing Motors)

Magnetic Center line distance from shaft shoulder

Magnetic Center line distance from all the way out mark

Magnetic Center line distance from all the way in mark

Total Motor End Float

Additional photos





Yes, the shaft has been isolated for delivery.

Service Tech name: Robert Wiley

Service Tech signature:

Rober Wiley